

	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425	2426	2427	2428	2429	2430	2431	2432	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

of

and

for

LAW OFFICES
DAVID NEWMAN
CHARTERED
TENTH ANNUAL SQUARE
P.O. BOX 2728
PLATA, MD 20646
(301) 934-6100

CENTENNIAL SQUARE
P.O. BOX 2728
LA PLATA, MD 20646
(301) 934-6100

[0001]

BACKGROUND OF THE INVENTION

[0002] The apparatus being provided relates to the field of engineering physics, in particular, to the radiation detecting technique and may be used for photometry, dosimetry and also for measurements of the space-energy characteristics of optical and ionizing-radiation fields. The radiation detector used in optical radiation detection and photometry application is known [1]. The detector comprises a photodiode placed either in parallel with a load or connected in series with a bias voltage source and with a load in the simplified case [1]. A current or charge-amplifier input circuit is conventionally used therein as a load. One-dimensional and two-dimensional photodiode and phototransistor arrays [2,3], as well as image detectors based on the charge-coupled devices (CCD) [4] are also known. Said devices detect space-energy characteristics of optical radiation fields. The ionizing radiation detectors used for detection dosimetry and spectrometry of nuclear radiation are known [5]. The construction of said detectors is similar to that of optical radiation detectors, in which ionization chambers, proportional counters, semiconductor sensors, scintillation counters or photodiodes paired with scintillators are used instead photodiodes [5]. Ionizing-radiation coordinate-sensitive detectors (IRCSD) for making one-dimensional and two-dimensional coordinate analysis are known and used in the nuclear experiment techniques for detecting elementary particle traces and

5

10

20

measuring a spatial distribution of a nuclear particle flow
[6,7]. Said detectors make up either a system of wire electrodes
disposed in a common gas volume or a system of strip electrodes
sputtered on a silicon crystal surface and coupled with the
electronics for reading the coordinate information.

[0003] Of conventional radiation detectors, the detector
described in [1] is most similar to the detector being provided
by the engineering nature thereof. Said detector comprises a
photodiode, placed in parallel with the load or connected in
series with the load or the bias-voltage source. In this case,
the dc current or charge-amplifier input circuit serves as the
load. Said detector is intended to detect an optical radiation
and may be used to detect an ionizing radiation by coupling the
photodiode with a scintillator. A low sensitivity resulting from
the noises and zero drift of the dc amplifier used as the
detector load is a disadvantage of said detector.

[0004] The subject-matter of the first embodiment of the
invention being claimed is that in the radiation detector
comprising a series-connected photodiode and a load, with the
load being coupled with the photodiode through a signal contact
and at the other side being connected to a common bus; a
transistor and an interrogation pulse generator are additionally
incorporated, with the second photodiode electrode being coupled
with the first electrode of the transistor, a control electrode

of which is coupled with the interrogation pulse generator output, and the third transistor electrode is coupled with the common bus. In addition, N groups of elements, each consisting of the series-connected photodiode and transistor, are placed in parallel with the load, and the interrogation pulse generator comprises N outputs, each being coupled with the transistor control electrode from the respective element groups, where N - integer > 1. Alternatively, the detector may comprise L loads, with the N_i groups of elements being placed in parallel with each i-th load, and the total number of groups of elements in the detector being equal to the number N of outputs of the interrogation pulse generator, where L - an integer >1 and N_i - positive integer. Additionally, capacitors are placed in parallel with photodiodes.

[0004] The subject-matter of the second embodiment of the invention being claimed is that the radiation detector comprising a radiation sensitive element and the load, with the sensitive element connected at one side to a voltage supply bus and the load being connected at one side to a common bus, additionally comprises a switching-type transistor, a capacitor and an interrogation pulse generator, with the sensitive element being connected at the other side to the first transistor electrode and the first plate of the capacitor, the second plate of which is connected to the load signal contact, and the output of interrogation pulse generator being connected to the control electrode of the transistor, the third electrode of which is

connected to the common bus. Besides, N groups of elements is connected between the supply voltage bus and the common bus, and each group comprises the series-connected radiation sensitive element and the transistor, the common point of which is coupled with the load signal contact through the capacitor, and the interrogation pulse generator comprises N outputs, each being connected to the transistor control electrode from the respective group of elements, where N - integer > 1.

Additionally, the detector may comprise L loads, with the signal contact of each i-th load being connected to N_i groups of elements, and the total number of groups of elements in the detector equals the N number of interrogation pulse generator outputs, where L - integer > 1, and N_i - positive integer. In addition, a resistor is connected between the sensitive element and the common point of the switching-type transistor and capacitor.

[0005] The subject-matter of the third embodiment of the invention being claimed is that the radiation detector comprising a radiation sensitive element and a load, with the sensitive element being connected at one side to a supply voltage bus and the load being connected at one side to a common bus, additionally comprises a transistor and an interrogation pulse generator, with the sensitive element being connected at the other side to the first transistor electrode, the output of the interrogation pulse generator being connected with the control electrode of the transistor, the third electrode of

which is connected to the load signal contact. In addition, a capacitor is connected between the first transistor electrode and common bus, and a resistor is connected between the first transistor electrode and the sensitive element.

5 [0006] SUMMARY OF THE INVENTION

[0007] The object of the invention being claimed is to increase sensitivity and accuracy in detecting radiation intensity and also to expand a dynamic range of radiation intensities to be detected.

10 [0008] The accuracy and sensitivity in measuring the
radiation intensity in the first embodiment of the invention
being claimed comprising a series-connected photodiode and a
load as in prior art is increased by incorporating additionally
a switching-type transistor and an interrogation pulse generator
15 into the detector, with the respective connections of said
elements to the other detector elements being provided. As a
result, a photodiode photocurrent is converted from the direct
photocurrent to the pulse photocurrent, which small quantity can
be measured at a higher accuracy due to the fact that the
20 current amplifies and charge pulse amplifiers do not comprise
low-frequency noise components, such as flicker and zero drift,
that are characteristic of dc current amplifiers. Placing N
groups of elements consisting of a transistor and a photodiode
coupled with N outputs of the interrogation pulse generator in
parallel with the load provides a new quality to the radiation

detector, i.e. a capability of analyzing the spatial
distribution of intensity of the to-be-detected radiation. In
comparison with the conventional one-dimensional photodiode
strips [3] the embodiment being claimed allows for achieving a
wider dynamic range of radiation intensities to be detected.
This is conditioned by the fact that the dynamic range
determined as the ratio of the maximum registered radiation
intensity to the minimum one is defined by the range of an
electric charge integrated at the photodiode capacitance and by
the integrating period range of said charge. The range of the
charge integrated at the photodiode capacitance is determined as
the ratio of a maximum value of the integrated charge to the
noise charge of the amplifier detecting said charge. All other
factors being equal, the range of the charge integrated at the
photodiode capacitance is directly proportional to the square
root of the capacitance value thereof, since the maximum value
of the charge integrated at the photodiode increases in direct
proportion to the capacitance value thereof, whereas the value
of the noise charge of the amplifier increases in direct
proportion only to the square root of the capacitance value at
the input thereof [5]. The period range of photocurrent
integrating at the photodiode capacitance in its turn is
determined by the ratio of the maximum value thereof to the
minimum one. The maximum duration of the photocurrent
integrating period is determined by the leakage resistance of
the photodiode, transistor and circuit board insulation and

increases directly with the increase in the total capacitance of the photodiode and switching-type transistor. The minimum duration of the photocurrent-integrating period is determined by the time constant of the total capacitance discharge of the photodiode and switching-type transistor during the process of forming of an integrated discharge readout signal. The duration of said time constant is directly proportional to the total capacitance of the photodiode and switching-type transistor and to the switch-on resistance of the switching-type transistor. Therefore, the larger the capacitance of the photodiode and the charge leakage resistance therefrom, as well as the lower the switch-on resistance of the switching-type transistor, the more extensive the dynamic range of radiation intensities to be detected. The embodiment being claimed is characterized in that both field-effect transistors similar to the conventional photodiode strips and bipolar transistors may be used as the detector switching-type transistors. Using bipolar transistors, the steepness of which exceeds hundreds of times that of field-effect transistors, as switching-type transistors of the detector being claimed allows the switch-on resistance of the switching-type transistor to be decreased hundreds-fold and, respectively, the dynamic range of to-be-detected radiation intensities to be expanded hundreds-fold. To produce the preset dynamic range of the radiation intensities to be detected, the capacitors of the required capacitance are placed in parallel

with the photodiodes. To reduce the amplifier noises, the detector may contain L loads.

[0009] Increasing sensitivity and accuracy in detecting the radiation intensity in the second embodiment of the invention being claimed including a radiation-sensitive element and a load like in the prior art is attained by additionally incorporating a transistor and an interrogation pulse generator into the detector, with the respective connections of said elements to the other detector elements being provided. Connecting N groups of elements consisting of the switching-type transistor, a radiation-sensitive element and a capacitor, which are connected to the N outputs of the interrogation pulse generator, between the supply voltage bus and common bus provides a new quality to the radiation detector, i.e. a capability of analyzing the intensity spatial distribution of the radiation to be detected. The second embodiment of the detector being claimed (like the first embodiment) allows for achieving a more extensive dynamic range of radiation intensities to be detected, compared with the conventional one-dimensional photodiode strips, as well as allows for using radiation-sensitive elements such as proportional counters, ionizing chambers, photoresistors, etc. requiring high supply voltage and, as a result, expanding the range of possible detector applications. The increase in sensitivity and accuracy in detecting the radiation, as well as the expansion of the dynamic range of the radiation intensities to be detected is achieved in the second embodiment being

claimed due to the action of factors leading to attaining similar technical results in the first embodiment being claimed. To reduce amplifier noises, the detector may contain L loads.

5 [0010] Increasing sensitivity and accuracy in detecting the radiation intensity in the third embodiment of the invention being claimed including a radiation-sensitive element and a load like in the prior art is attained by additionally incorporating a switching-type transistor and an interrogation pulse generator into the detector, with the respective connections of said
10 elements to the other detector elements being provided. The increase in sensitivity and accuracy in detecting the radiation is achieved in the third embodiment being claimed due to the action of factors leading to attaining similar technical results in the first embodiment being claimed. To achieve the preset dynamic range of the radiation intensities to be detected, a capacitor of the required capacitance is connected between the first switching-type transistor electrode and common bus.

[0011] BRIEF DESCRIPTION OF THE DRAWINGS

20 [0012] Figs. 1, 2, 3 show three modifications of an electric circuit of the first embodiment of the radiation detector being claimed that uses photodiodes as sensitive elements.

[0013] Figs. 4, 5, 6 and 7 show four modifications of an electric circuit of the second embodiment of the radiation detector being claimed that uses different types of sensitive

elements and operates when a bias voltage, including high bias voltage, is supplied thereto.

[0014] Figs. 8 and 9 show two modifications of an electric circuit of the third embodiment of the detector being claimed that uses different types of sensitive elements operating when energized by a bias voltage.

[0015] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0016] A radiation detector being provided comprises an interrogation pulse generator 1, a radiation sensitive element 2 (a photodiode in the first embodiment of the detector being provided), a switching-type transistor 3 and a load 4. In the second and third embodiments, the detector may also include a current-limiting resistor 5. In the first detector embodiment (see Figs. 1, 2, 3) the photodiode 2 and load 4 are series-connected, with the load 4 being coupled through a signal contact with the photodiode 2 and with the common bus at the other side. The second electrode of the photodiode 2 is coupled with the first electrode (for example, emitter) of the switching-type transistor 3; the control electrode (for example, base) is coupled with an output of the interrogation pulse generator 1 through a resistor 6; and the third electrode of the transistor 3 (for example, a collector) is coupled with the common bus. An integrating capacitor 7 may be placed in parallel with the photodiode 2. In the second modification of the first detector embodiment (see Fig. 2), N groups of $8_1, 8_2, \dots, 8_N$

elements, each consisting of the series-connected switching-type transistor 3 and photodiode 2, with which the integrated capacitor 7 may be placed in parallel, is connected across the load 4. Besides, the interrogation pulse generator 1 comprises N outputs, each being connected to the control electrode (base) of the switching-type transistor 3 from the respective group of elements via resistor 6, where N - integer > 1 . In the third modification of the first detector embodiment (see Fig. 3), L loads $4_1, 4_2, \dots, 4_L$ are included, with above-mentioned N_i group of elements being placed in parallel with each i -th load, and the interrogation pulse generator 1 comprising N outputs, the number of which equals the total number of groups of elements in the detector, where L - positive integer > 1 , and N_i - positive integer.

[0017] In the second embodiment of the detector being provided (see Figs. 4, 5, 6, 7), another types of elements, for example, ionization chambers (see Fig. 4) or ionizing radiation proportional counters (see Fig. 5, 6, 7) may be also used in addition to photodiodes as sensitive elements 2. The first simplest modification of the second embodiment of the detector being provided (see Figs. 4, 5) includes an interrogation pulse generator 1, a radiation sensitive element 2, a switching-type transistor 3, a load 4, a current-limiting resistor 5 and an integrating capacitor 7. In this case, the radiation sensitive element 2 is coupled with the supply voltage bus at one side and, via the current limiting resistor 5, with the first

electrode (for example, a drain region or emitter) of the switching-type transistor 3 and the first plate of the integrating capacitor 7 at the other side, the second plate of the latter being connected to the signal contact of the load 4, the second contact of which is coupled with the common bus. Besides, the output of the interrogation pulse generator 1 is coupled with the control electrode (gate or base) of the switching-type transistor 3. It should be noted, that in case a bipolar transistor serves as the switching-type transistor 3, the resistor 6 is connected between the generator 1 output and transistor 3 base (see Fig. 5). The third electrode (for example, source or collector) of the switching-type transistor 3 is coupled with the common bus. A constant voltage \hat{A}_1 of the required polarity and value is supplied to the supply voltage bus. Both field-effect transistors (see Fig. 4) and bipolar transistors (see Fig. 5) may be used as the switching-type transistor 3.

[0018] In the second embodiment of the detector being provided, it is most reasonable to use elements sensitive to various radiation types needing the bias voltage, including high bias voltage, to be supplied for an efficient operation. In the second modification of the second embodiment of the radiation detector being provided (see Fig. 6), N groups of $8_1, 8_2, \dots, 8_N$ elements, each consisting of a series-connected radiation-sensitive element 2 and a switching-type transistor 3, the common point of which being coupled with the signal contact of

the load 4 via the integrating capacitor 7, are connected between the supply voltage bus and common bus. Besides, the interrogation pulse generator 1 comprises N outputs, each being coupled with the control electrode (base) of the switching-type transistor 3 via the resistor 6 from the respective group of elements, where $N - \text{integer} > 1$. In the third modification of the second radiation detector embodiment (see Fig. 7) L loads $4_1, 4_2, \dots, 4_L$ are included with the signal output of each i-th load is connected to the above-mentioned N_i groups of elements, and the interrogation pulse generator contains N outputs, the number of which equals the total number of groups of elements in the detector, where $L - \text{integer} > 1$ and $N_i - \text{positive integer}$. In the third embodiment of the radiation detector being provided (see Figs. 8, 9), the other types of sensitive elements 2 requiring a bias voltage supply for an efficient operation, for example, for photoresistors (see Fig. 8), may be also used in addition to photodiodes. The first simplest modification of the third embodiment of the detector being provided (see Fig. 8) comprises an interrogation pulse generator 1, a radiation-sensitive element 2, a switching-type transistor 3, a load 4 and a current-limiting resistor 5. In this case, the radiation-sensitive element 2 is coupled at one side with the voltage supply bus and at the other side - with the first electrode (for example, drain) of the switching-type transistor 3 via the current-limiting resistor 5. The output of the interrogation pulse generator 1 is coupled with the control electrode (gate)

of the switching-type transistor 3, the third electrode of which (for example, source) is coupled with the signal contact of the load 4 connected to the common bus at the other side. A constant voltage \hat{A}_1 of the required polarity and value is delivered to the voltage supply bus. The second modification of the third radiation detector embodiment (see Fig. 9) additionally comprises an integrating capacitor 7, being connected between the first electrode (for example, drain) of the switching-type transistor 3 and common bus. Field-effect transistors, the self-capacitance of which is used as an integrating capacitance in the first modification of said detector embodiment, may be used as the switching-type transistor 3 only in the third embodiment of the radiation detector being provided.

[0019] The radiation detector provides the interrogation pulse generator 1 being a rectangular voltage-pulse generator. The amplitude and polarity of output voltage pulses are selected to enable the respective detector switching-type transistors thereby. Ring counters, decoders, shift registers and other devices having the number of outputs equaling those of switching-type transistors in the detector and forming the voltage pulses of the required polarity, amplitude and duration on outputs at the respective points of time may be used as the generator 1 in multi-element detector modifications. The generator 1 frequency sets the integrating period of the radiation recorded by the detector and defines the limit of the intensity registered.

[0020] The operation of the radiation detector is described below.

[0021] The current of the sensitive element 2, when exposed to radiation, integrates at the common capacitance of the sensitive element 2 and paralleled integrating capacitor 7 (see Figs. 1, 2, 3), at the capacitance of the integrating capacitor 7 (see Figs. 4-7), at the self-capacitance of the switching-type transistor 3 and integrating capacitor 7 (see Fig. 9) during the time between interrogations of the transistor 3. An interrogation voltage pulse with polarity activating the transistor 3 is supplied from the generator 1 output to the transistor 3 control electrode at the time the switching-type transistor 3 is being interrogated. As a result of activation of the transistor 3, a current pulse carrying a charge integrated at the capacitor 7 (as well as at the capacitance of the sensitive element 2 or at the capacitance of the transistor 3) through the capacitor 7 and load 4 flows therethrough. While supplying the interrogation pulse, interelectrode-capacitance recharging charges flow via the load 4, via the capacitance of the sensitive element 2 and/or integrating capacitor 7 (see Figs. 1-7) or directly (see Figs. 8, 9) The charges equal in value, but opposite in sign flow via said circuits upon removing the interrogation parts. As a result, after supplying each interrogation pulse, a total charge flows through the load 4 equaling the charge of said element integrated at the capacitor 7 and/or at the self-capacitance of the sensitive element 2 over

the time interval between supplying the interrogation pulse. In case the load 4 is connected between the switching-type transistor 3 and common bus (see Fig. 8, 9), after supplying the interrogation pulse, the charge of the sensitive element 2 integrated at the total capacitance of the capacitor 7 and/or transistor 3 is carried to the load 4. Said charge is proportional to a radiant flux incident on the sensitive element 2 over the time interval between interrogations of the respective switching-type transistor 3.

[0022] In multi-element modifications of the detector (see Figs. 2, 3, 6, 6), the interrogation pulse generator 1 is provided with a plurality of outputs, with voltage pulses forming on each of them in a preset sequence. In this case, a serial interrogation of switching-type transistors 3, which are included into the groups of elements 8, corresponding, for example, to a sequential reading out of the respective integrating capacitors 7, is performed, while a sequence of current pulses, displayed as video signals, form at the load 4, when synchronizing clock is added thereto at the respective instant of time. It should be noted that the coordinate of the detector sensitive element is uniquely defined by the number of the load pulse corresponding thereto or by the time said pulse is generated, while the number of radiation particles detected in said sensitive element is defined by the amplitude of the current pulse corresponding thereto. In the detector modifications having plurality of loads (see Figs. 3, 7), the

sequence of interrogation current pulses forms serially at each load at time intervals of interrogation of switching-type transistors incorporated into the groups of elements 8 coupled with said load. Availability of a plurality of loads in the detector allows the total number of sensitive elements to be increased in the detector without increasing the noise of amplifier integrating capacitors detecting the readout signals. In addition to the increased radiation detection sensitivity, the capability of the detector being provided to analyze space-energy characteristics of various types of radiation fields to be detected within an extensive intensity range significantly expands functional capacities and application field thereof. The invention may be used in the fields of nuclear physics, dosimetry, radiation flaw inspection, photometry, crystallography, medicine and other fields of science and engineering.

References

1. J. Witson. 500 Practical IC-Based Circuits: transl. from English. -M.: Mir, 1992, 278 p., p. 88.
2. V.F. Zolotarev. Vacuumless Analogs of Television Cathode Ray Tubes: --M.: Energia, 1972, 216 p.
3. Semiconductor Image Sensors. Ed. P. Yespers, F. Van de Vile and M. White: transl. from English.-M.: Mir, 1979, 573 p.
4. Charge-Coupled Devices: transl. from English/Ed. D.F. Barb.-M.: Mir, 1982, 240 p.

5. A.P. Tsitovich. Nuclear Electronics.: --M.: Energoatomizdat, 1984, pp.5-33.
6. Yu.V. Zanevsky. Elementary Particle Wire Detectors: --M.: Atomizdat, 1978.
7. R. Klenner. Silicon Detectors. Nuclear Engineering Abroad, 1986, No.6, pp.35-40.

5

604 224 660

LAW OFFICES
DAVID NEWMAN
CHARTERED
CENTENNIAL SQUARE
P.O. BOX 2728
LA PLATA, MD 20646
(301) 934-6100